



GPS Networking Link Budget Calculator

The following spreadsheet calculates the effective radiated power for a GPS Networking reradiating system as well as the effective signal power at given range in dBm. Enter the components for the strongest repeating path in your system into the section with the **red** border. NTIA regulations require that the repeated signal be weaker than -140 dBm when measured 100 FT outside of the reradiated structure. Please feel free to reach out to GPS Networking if you need assistance.

<i>Receiving Antenna Gain</i>	<i>Antenna Cable Insertion Loss</i>	<i>System Gain</i>	<i>Nominal Antenna Gain Best Case</i>	<i>Distance to Nearest External Wall (FT)</i>	<i>Signal Power at Nearest External Wall Building</i>	<i>Signal Power at 100' Outside of Nearest External Wall In dBm</i>
35	-3.00	15	3.5	42.5	-138.16	-148.67
GPS Carrier Frequency MHz			Total System Gain	Range in Miles	Total Signal Power @ Range in Watts	
L1: 1575.42			50.5	0.01	15.3E-18	
Avg Receive Power dBm North America				Range in Meters	Radiated Power dBm	
-130				12.95	-79.5	
Free Space loss with Isotropic Antennas				Range in Kilometers	Power (pW)	
-58.66				0.01	5.62	
Helpful Links:					Effective Radiated Power (pW)	
Get an FCC Registration Number					11.22	
FCC Experimental Broadcast Form 442					Effective Radiated Power (dBW)	
Cable Loss Calculator					-109.5	
GPS Networking Store						
Email Tim Waite for help						



Distance to External Wall (FT): 42.5 ft

System Receive Antenna

Part Number	Gain/Loss (dB)
L1GPSA	35

Passive Components (Cause Loss)

Part Number	Gain/Loss (dB)
-------------	----------------

Amplified Components (Cause Gain)

Part Number	Gain/Loss (dB)
HNRRKIT	15

Repeating Antennas

Part Number	Gain/Loss (dB)
L1GRRKPA	3.5

Cable Runs

[illegible]

System Diagram

